

# Contour 21 Splash 50cm Schools basin with overflow - one taphole

## ILLUSTRATED

- S2690** Contour 21 Splash 50cm Schools basin with overflow - one taphole
- E7840** Concept small semi-pedestal
- E0157** Wall fixing set
- B8263** Avon 21 1 hole washbasin mixer , self closing push button, variable temperature control with 15mm female connector flexible hoses on inlets. Flow regulated to 3.7 litres per minute maximum to comply with Water Technology List requirements.
- S8722** Waste 1¼" brass strainer waste, 80mm slotted tail

## OPTIONS

- A4852** Sensorflow 21 compact washbasin mounted spout with integral sensor, 3.7 litre per minute aerated spray outlet, combined inlet servicing valve and filter, mains
- A4853** Sensorflow 21 compact washbasin mounted spout with integral sensor, 3.7 litre per minute aerated spray outlet, combined inline servicing valve and filter, link
- A4851** Sensorflow 21 compact washbasin mounted spout integral sensor servicing valve and filter, copper tube inlets, battery
- S8920** Trap 1¼" plastic resealing bottle, 75mm seal, multi-purpose outlet
- S8900** Trap 1¼" metal bottle, 75mm seal, outlet screwed 1¼" BSP male with compression nut and ring



## FEATURES



## ILLUSTRATED PRODUCT DETAILS

<b>Sizes</b>	<b>Finishes</b>
<b>S2690</b> w:500 x d:401	<b>S2690</b>  White (01)
<b>Weights</b>	<b>E7840</b>  White (01)
<b>S2690</b> 11.50 KG	<b>E0157</b>  Neutral / No Finish (67)
<b>E7840</b> 5.58 KG	<b>B8263</b>  Chrome (AA)
<b>E0157</b> 0.16 KG	<b>S8722</b>  Chrome (AA)
<b>B8263</b> 2.30 KG	<b>Capacity</b>
<b>S8722</b> 0.22 KG	<b>S2690</b> 4.0 litres
<b>Materials</b>	<b>Flow rates</b>
<b>S2690</b> Vitreous China	<b>B8263</b> 3.7 Litres per minute @ 3 bar pressure
<b>E7840</b> Fine Fireclay	
<b>E0157</b> Metal	
<b>B8263</b> Chrome Plated Brass	
<b>S8722</b> Chrome Plated Metal	

### Special Notes

Recommended fixing heights (floor to front rim);  
 Nursery use 600mm  
 Infant use 700mm  
 Junior use 750mm  
 Senior/adult use 780-800mm.  
 Washbasin wall mounted using E015767 wall fixing set or panel mounted using E006267 fixing set